# **Panasonic**

# **AW-HEA10W/K**

**Control Assist Camera** 

For indoor use







# Easy Camera PTZ Control from iPad

The Control Assist Camera supports flexible and intuitive operation of a HD Integrated Camera\*1 by allowing wireless control from an iPad\*2. PTZ control is possible with just a single tap on the panoramic view of the scene. Allows up to 100 sets\*3 of cameras to be registered in a single iPad and the camera can be switched during the operation.

### Ultra wide angle full HD live images to assist control

A 1/4.37 type (effective size) 3.91 megapixel MOS sensor and a singlefocus 95º horizontal ultra wide angle lens enable wide and clear overview shots to assist control of HD Integrated Cameras.

### Easy operation by the free | "PTZ Cntrl" app for iPad





Download the free "PTZ Cntrl" app for iPad and install it to enable wireless control of the camera from the iPad. Operations can be made by touching the screen of the overall image from the Control Assist Camera and an image from an HD Integrated Camera.

## [Basic system and operations]



#### Camera control functions\*4

HD Integrated Camera's pan, tilt, zoom control and camera setting adjustment such as image quality or frame rate can be done from an iPad. Allows up to 100 sets\*3 of cameras to be registered in a single iPad and the camera can be switched during the operation.

Display the camera in control.

Control the zoom of the HD Integrated Camera by the slide bar.

Configure settings for the HD Integrated

- [Settings available]
- -Focus (Auto, Manual)
- -Iris (Auto, Manual)
- -Gain (OdB, 3dB, 6dB, 9dB, 12dB, 15dB,
- 18dB, Auto)
- -Resolution (Low, Middle, High) -Frame Rate (Low, Middle, High)
- -Calibration (Positioning of the images from HD Integrated Camera and Control Assist Camera)
- -Camera reset (power ON/OFF)



<Image from HD Integrated Camera> Tapping the screen to set the spot to the center and by dragging the position you can change the camera angle. Pinch out to zoom in, pinch in to zoom out, using this enlarged display allows you to adjust the angle

<Image from Control Assist Camera> Tapping and dragging the overall image moves the display to the target for capture by the HD Integrated Camera. You can even visually decide the field of view by placing two fingers on the screen. Changing the distance between the two fingers controls the field of view.

# Preset memory function for smooth operation

The camera shooting angle can be set in advance with the preset memory function. Tapping and holding the number button saves up to nine setting configurations. Preset can be recalled by just tapping the number.



\*1: AW-HE130W/K, AW-HE40 Series, and AW-HE60S/H only. When used with the AWHE60S/H, in some cases an AW-HE60S/H software upgrade will be necessary. For details, see "Support & Download" on the Panasonic website (http://pro-av.panasonic.net/en/). \*2: An iPad is required (sold separately). The "PTZ Cntrl" app for iPad (free download from the App Store) is required. See website (http://pro-av.panasonic.net/ en/sales o/camera/aw-hea10/ ) for details. \*3: When HD integrated cameras and Control Assist Cameras are combined. \*4: Only functions supported by AW-HE130, HE40, and HE60 can be controlled.

# Flexible setup and two color variations to choose from

Cameras can be set up suspended from the ceiling or standing, depending on the operating environment. The camera angle is manually adjustable with a pan range of  $\pm 30^\circ$  and a tilt range of  $\pm 45^\circ$ . Two color variations are also available: white and black. Select the setup type and color according to the intended application and environment.

# PoE\*5 support for less cabling and reduced installation cost

Connection to network devices supporting PoE (IEEE 802.3af compliant) allows power to be supplied via an Ethernet cable. This eliminates the need for power supply construction and laying power cable, allowing for fewer cords when installing and reduced installation expenses.



### **HDMI** output

The HDMI output allows you to use the video captured by the Control Assist Camera by outputting to devices equipped with HDMI. Multiple formats\*6 are supported (1080/59.94p, 1080/50p, 1080/59.94i, 1080/50i, 720/59.94p, 720/50p, 480/59.94p, and 576/50p signals).


## [Application Examples]

#### Parliaments

# When combined with a Control Assist Camera, there are even more uses for HD integrated camera

Even the unexpected remarks of a participant without a preset position can be quickly handled with intuitive operations. In combination with wide-angle video with an overall view, it is possible to sensitively capture video suitable for constantly changing assembly sessions.







#### **Tour Courses**

In places like zoos, by shooting the animals' overall space, it is possible to easily find the constantly moving animals themselves. For places that are difficult to see from the tour course, the staff can manually operate the camera while giving easy-to-understand explanations using a large-screen monitor.



### Symposium / Lecture Capture

Excellent for use in situations (lectures, etc.) where the speakers have not been defined in advance. The camera can be quickly and easily controlled to zoom in on random speakers whose positions have not been preset.





#### **TV Conferences**

With one iPad, even participants can control the HD integrated camera for lively teleconferencing. With the wide-angle view, it is possible to quickly capture the speaker with just a tap.

<sup>\*5:</sup> Abbreviation of Power over Ethernet

<sup>\*6:</sup> Output to iPad is 640 x 360 or 320 x 180.

**Specifications** As of April, 2015

| General     | Power requirements   | 5.0 V DC/0.86 A (when using AC adaptor)<br>44 - 57 V DC/0.14 A (PoE power supply)   | Camera Unit               | Standard illumination   | 1,400 lx  |
|-------------|--|---|---------------------------|---|---|
|             | · ·  |   |                           | Minimum illumination  | Approx. 20 lx (1/60 in auto mode)   |
|             | Allowable operating temperature  | 0°C to 40°C (32°F to 104°F)   | Input/Output<br>Connector | HDMI  | HDMI connector  HDCP is not supported.  Viera Link is not supported.  |
|             | Allowable relative   | 10% to 80% (no condensation)  |                           |   |   |
|             | humidity   | · ·   |                           | Network   | 10BASE-T/100BASE-TX,<br>RJ-45 connector, Automatic recognition of straight/crossover<br>cable   |
|             | Unit weight  | Approx. 0.9 kg (1.98 lb) (excluding mounting brackets)  |                           |   |   |
|             | Dimensions (W x H x D)   | 183 mm x 65 mm x 225 mm<br>(7-3/16 inches x 2-9/16 inches x 8-7/8 inches)   |                           | uco   |   |
|             |  |   |                           | USB   | Mini-B port: Used for maintenance   |
| Camera Unit | 1/2.33-inch MOS solid-state image sensor<br>(Effective size of image sensor: 1/4.37-inch)<br>Image sensor Total pixels: Approx. 15.3 million<br>Effective pixels<br>Video: Approx. 3.91 million (16:9) |   |                           | SD Memory Card  | microSD card slot: Used for maintenance   |
|             |  | "PTZ Cntrl" compatible devices and operating systems  |                           | Supported devices: iPad<br>Supported operating systems: iOS 8.1 |   |
|             |  | Video: Approx. 3.91 million (16:9)  | Standard Accessories      |   | Mounting bracket A (for mounting this unit): 1, Mounting bracket B (for securing this unit, for AW-HE130): 2, Mounting bracket C (for AW-HE40 Series): 1, Drop-prevention wire: 1, Drop-prevention wire mounting screw M4 x 8 mm: 1, Bracket mounting screws A M4 x 10 mm: 8, Bracket mounting screws B M3 x 6 mm: 4, AC adaptor: 1, Power cable: 1 |
|             | Lens   | F2.0 (f = 2.15 mm)<br>35 mm equivalent; Approx. 18.0 mm (16:9)<br>Field of view: 95° (horizontal), 56° (vertical) [When zoom is 1x] |                           |   |   |
|             | Shutter speed  | 1/60 to 1/12000   |                           |   |   |
|             | White balance  | ATW, Sunny, Cloudy, Indoor1, Indoor2, AWB A, AWB B  |                           |   |   |

#### Rear view



#### Option

Direct Ceiling Mount Bracket

WV-Q105A



### Lineup of cameras compatible with the AW-HEA10W/K Control Assist Camera (for indoor use)



- \* When used with the AWHE60S/H, in some cases an AW-HE60S/H software upgrade will be necessary. For details, see "Support & Download" on the Panasonic website (http://pro-av.panasonic.net/en/).
- Microsoft®, Windows®, Windows® 7, Windows® 8, Windows® 8.1 and Internet Explorer® are either registered trademarks or trademarks of Microsoft Corporation in the United States and other countries.
- Apple, Mac, OS X, iPhone, iPod Touch, iPad, and Safari are registered trademarks of Apple Inc., in the United States and other countries.

# anasonic

#### Panasonic Corporation

AVC Networks Company 2-15 Matsuba-cho, Kadoma, Osaka 571-8503

http://pro-av.panasonic.net/

#### [Countries and Regions]

Argentina

Australia Bahrain

+55 11 3889 4035 +1 905 624 5010 +86 10 6515 8828 Brazil Canada China +852 2313 0888 +421 (0) 903 447 757 Hong Kong Czech Republic: Denmark +45 43 20 08 57 +20 2 23938151 Egypt Finland, Latvia, Lithuania, Estonia +358 (9) 521 52 53 +33 (0) 1 47 91 64 00 France Germany, Austria, Switzerland +49 (0) 6103 313887 Greece +30 210 96 92 300 Hungary +36 (1) 382 60 60 +91 1860 425 1860 India Indonesia +65 6277 7284 Iran (Vida) +98 21 2271463 (Panasonic Office)+98 2188791102 +39 02 6788 367 Italy Jordan +962 6 5859801 Kazakhstan +7 727 298 0891 Korea Kuwait ±82 2 2106 6641 +96 522431385

+54 11 4122 7200

+61 (0) 2 9491 7400 +973 252292

+96 11665557 Lebanon +60 3 7809 7888 +52 55 5488 1000 Malaysia Mexico Netherlands, Belgium

+31 73 640 2729 New Zealand +64 9 272 0100 Norway Pakistan +47 67 91 78 00 +92 5370320 (SNT) +972 2 2988750 +507 229 2955 Palestine Panama

Philippines

+48 (22) 338 1100 +351 21 425 77 04 Poland Portugal Romania, Albania, Bulgaria, Macedonia +40 (0) 729 164 387 Russia & CIS +7 495 9804206

+65 6277 7284

+96 626444072 +65 6277 7284 Saudi Arabia Singapore

Sloyak Republic, Croatta, Serbia, Bosnia, Montenegro, Slovenia +421 (0) 903 447 757 South Africa +27 11 3131622 Spain +34 (93) 425 93 00 +46 (8) 680 26 41 +963 11 2318422/4 Sweden Svria Taiwan Thailand +886 2 2227 6214 +662 731 8888

+90 216 578 3700

Turkey +90 216 376 C.
U.A.E. (for All Middle East)
+971 4 8862142
+380 44 4903437
+391 424 70 69 U.K. U.S.A. +44(0)1344 70 69 13 +1 877 803 8492 +65 6277 7284



JQA-0443



Factories of AVC Networks Company have received certification. (Except for 3rd party's peripherals.)